

Model	AC Output/Capacity	Specification(Output)	Highlight	Package Includes(Standard)	Accessories (Optional, Sold Separately)
AC300 	3000W (100V/120V) 6000W (220V-240V, *2 AC300) No Battery 3072-12288Wh (100V/120V, *1-4 B300) 6144-24576Wh (220V-240V, *2-8 B300)	6* AC 100V/120V 1* NEMA TT-30 2* 5V/3A USB-A 2* 18W USB-A 1* 100W USB-C PD3.0 1* 12V/30A Super DC 1* 24V/10A Car Port 2* 15W Wireless Charging Pad	1. Battery and Inverter are standalone 2. Capacity up to 12288Wh/3000W(100V/120V Single Phase) 4576Wh/6000W(200V/240V Split Phase) 3. Four UPS Modes(Peak-load-shifting within) 4. App Remote Control(Wi-Fi & Bluetooth) 5. 2400W Dual PV Input, Built-in MPPT 5400W Fast recharge(AC 3000W+Solar 2400W) 6. Multi-recharge ways: AC, Solar, Car, Generator, Lead-acid Battery, EV, Wind Turbine, Roof Solar 7. Hot-swapping	AC300 Power Station AC Charging Cable Multifunctional DC Charging Cable (Solar, Car, Lead-acid Charging) Car Charging Cable Warranty Card User Manual	Sub Panel 30A AC Charging Cable 12V/30A RV Cable PV Drop Down Module(D300S) T500 500W Adapter 100W USB-C to USB-C Lead-acid Battery Charging Clamp
3-5 PV120/200 Panels					
B300 	No Inverter 3072Wh	1* 100W USB-C PD3.0 1* 12V/10A Car Port 1* 18W USB-A QC3.0	1. 3072Wh, LiFePO4 Expandable Battery, 3500+ Life Cycle 2. Compatible with AC200P/MAX, AC300, EB200P, EB150/240, EP500/Pro (Tips: Required Bluetti's Accessory P090D) 3. 500W AC Charging, 200W Solar or Car Charging 4. Dual Recharge: 700W(AC+Solar or PV) 5. Hot Swapping 6. App Control(connected with Main battery)	B300 Battery Pack Battery Expansion Cable(P090A) PV Input Cable(MCA-XT190, 10A/200W Max) User Manual Warranty Card	Car Charging Cable Lead-acid Battery Charging Clamp D050S DC Charging Enhancer D050S Lead-acid Charging Cable USB-C to USB-C Cable Cigarette Lighter Cable-5521 Cable 500W AC Adapter P090D External Battery Connection Cable
1 PV120/200 Panel					
EP500Pro 	3000W (100V/120V) 6000W (220V-240V, *2 EP500Pro) 5120Wh (100V/120V) 10240Wh (100V/120V, *2 EP500Pro)	4* 100V/120V AC 1* AC 120V 30A NEMA L14-30(JP/US) or 3*230V AC(EU/UK/AU) 3* 12V/10A DC 2* USB-A 2* USB-A (Quick Charge 3.0) 2* 100W USB-C 1* 12V/30A RV 2* Wireless Charging Pad	1. 5120Wh, LiFePO4, 6000+ Life Cycle 2. Split Phase 6000W@240V 3. Four UPS Modes(Peak-load-shifting within) 4. Dual Solar Recharging 2400W in total(2*1200W each) 12-150V, 12A, 1200W Max. for each circuit 5. AC+Solar fast recharge 4000W Max 6. Multi-recharge ways: Wall outlet/Solar/Car/Generator/Lead-acid Battery 7. App Remote Control/OTA Upgrade 8. In-grid Install	EP500Pro Power Station AC Charging Cable PV Charging Cable User Manual Warranty Card	Sub Panel 12V/30A RV Cable Generator Charging Cable Car Charging Cable T500 500W Adapter Fusion Box Pro(P030A) AC Charging Cable for Split Phase PV Drop Down Module(D300S) P090D External Battery Connection Cable Lead-acid Battery Charging Clamp
1-6 PV120/200 Panels					
EP500 	2000W (100V/120V) 4000W (220 - 240V) Surge 4800W 5120Wh (100V/120V, *2 EP500) 10240Wh (220-240V, *2 EP500)	4* 100V/120V AC(JP/US) or 3*230V AC(EU/UK/AU) 3* 12V/10A DC 2* USB-A 2* USB-A (Quick Charge) 1* 100W USB-C 1* 12V/30A RV 2* Wireless Charging Pad	1. 5120Wh, LiFePO4, 6000+ Life Cycle 2. Split phase 4000W Max@240V 3. Multi-recharge Ways: AC, Solar, Car, Generator 4. Solar input: 1200W, 55-145VDC, 20A Fully recharge in 4-7.5hrs, Built-in MPPT 5. Four UPS Modes(Peak-load-shifting within) 6. Fast Recharge: AC+Solar 1800W recharge simultaneously, Dual AC adapter recharge 1200W in total 7. App Remote Control, OTA Upgrade	EP500 Power Station AC Charging Cable PV Charging Cable User Manual Warranty Card	Sub Panel 12V/30A RV Cable Fusion Box(P020A) Generator Charging Cable D300S PV Step Down Module T500 500W Adapter
3-6 PV120/200 Panels					
AC200Max 	2200W Surge 4800W 2048Wh-6144Wh (*0-2 B230)	4* AC 100V/120V/230V(US/JP/UK/AU) 1* NEMA TT-30(only for US/JP) 2* 5V/3A USB-A 2* 18W USB-A 1* 100W USB-C PD3.0 1* 12V/30A Super DC 1* 12V/10A Car Port 2* 12V/10A DC5521 Outlets 2* 15W Wireless Charging Pad	1. LiFePO4 cell, 3500+ Life Cycle 2. Expandable with 1-2 *B230 / 1-2 *B300 3. Multi-Recharge Ways: AC, Solar, Car, Generator, Roof Solar, EV Charger, Wind Turbine, Lead-acid Battery 4. Solar input:900W/OCV 10-145V/15Amax 5. AC+Solar fast recharge 1400W max. Dual solar recharge 1400Wmax.(need accessory D050A) 6. App remote control(Bluetooth) 7. Hot-swapping	AC200MAX Portable Power Station T500 500W AC Adapter Charger Multi-functional DC Input Cable PV Charging Cable Car Charging Cable User Manual Warranty Card	12V/30A RV Cable Lead-acid Battery Charging Clamp B230 Expansion Battery Module B300 Expansion Battery Module P090D External Battery Connection Cable
3-5 PV120/200 Panels					
B230 	No Inverter 2048Wh	1* 100W USB-C PD3.0 1* 12V/10A Car Port 1* 18W USB-A QC3.0	1. External Battery Module, Compatible with AC200P/MAX, EB150/240, EB200P, EP500/Pro Tips: Need Bluetti's Accessory P090D 2. Multi-Recharge Ways: 500W AC, Solar 3. Hot Swapping 4. App Control(connected with AC200MAX)	BLUETTI B230 Battery Expansion Cable(P090A) User Manual Warranty Card	T500 500W AC Charger D050S DC Charging Enhancer D050S Lead-acid Charging Cable Cigarette Lighter Port to DC5521 P090D External Battery Connection Cable
AC200P 	2000W Surge 4800W 2000Wh	6* AC 110V/120V(JP/US) or 2* 220V-240V(EU/UK/AU) 4* 5V/3A USB-A 1* 60W USB-C 1* 12V/25A DC 2* 12V/3A DC 1* 12V/10A Car Port 2* Max 15W Wireless Charging Pad	1. LiFePO4 Cell, 3500+ Life Cycle 2. Solar Input: OCV 35-150V/900W/12A, Built-in MPPT 3. Fast recharge: AC+Solar 1200W, Dual AC adapter recharge 1000W 4. Multi-Recharge: AC Wall Outlet, Solar, Car, Generator, Lead-acid Battery 5. Expandable with B230/B300(need BLUETTI's accessory P090D)	AC200P Portable Power Station 500W AC Wall Charger XT90 to Aviation Plug(input) PV Solar Charging Cable Car Charging Cable User Manual	12V/25A RV Cable Connector for dual AC Converter Lead-acid Battery Charging Clamp Foldable Trolley Carry bag
3-5 PV120/200 Panels					
EB200P 	2200W Surge 4800W 2048Wh	6* AC 100-120V(JP/US) or 2* AC 220-240V(EU/UK/AU) 4* 5V/3A USB-A 1* 100W USB-C 1* 12V/25A DC 2* 12V/3A DC 1* 12V/10A Car port 2* Max 15W Wireless Charging Pad	1. Capacity:2048Wh, LiFePO4 cell 2. Solar Input: OCV 35-150V/900W/12A, Built-in MPPT 3. Fast recharge: AC+Solar 1200W, AC + AC 1000W 4. Multi-Recharge: AC Wall Outlet, Solar, Car, Generator, Lead-acid Battery 5. Expandable with B230/B300 (need BLUETTI's Accessory P090D)	AC200P Portable Power Station T500 500W AC Wall Charger XT90 to Aviation Plug(input) PV Solar Charging Cable Car Charging Cable User Manual	12V/25A RV Cable Lead-acid Battery Charging Clamp Connector for Dual AC Charging D300S PV Step Down Module Foldable Trolley Carry Bag
3-5 PV120/200 Panels					
EB70 	1000W (220-240V) 800W (100V/120V) Surge 1400W 716Wh	4* AC 100-120V(JP/US) or 2* AC 220-240V(EU/UK/AU) 2* 100W Max USB-C 1* 12V/10A DC Car Port 2* 5V/3A USB-A 2* 12V/10A DC 1* 15W wireless Charging 1* LED Lantern	1. LiFePO4 Cell with 2500+ Life Cycle 2. Solar Input: 200W, OCV 12-28V/8A, Built-in MPPT 3. Four Recharge Ways: Wall Outlet, Solar, Car, Generator 4. Charge 12 devices(US&JP) simultaneously Charge 10 devices(EU&AU&UK) simultaneously	EB70 Portable Power Station, AC Adapter & Charging Cable(90W or 200W for optional) Car Charging Cable Solar Charging Cable User Manual	None
1 PV120/200 Panel					
EB55 	700W Surge 1400W 537Wh	4* AC 100V-120V(JP/US) or 2* AC 220-240V(EU/UK/AU) 1* 100W USB-C 1* 12V/10A DC Car Port 4* 5V/3A USB-A 2* 12V/10A DC 1* 15W Wireless Charging 1* LED Lantern	1. LiFePO4 Cell with 2500+ Life Cycle 2. Solar Input: 200W, OCV 12-28V/8A, Built-in MPPT 3. AC+Solar last recharge 400W, fully recharge in 1.3-2.3hrs 4. Four Recharge Ways: Wall Outlet, Solar, Car, Generator	EB55 Portable Power Station AC Adapter(90W or 200W for optional) Solar Charging Cable Car Charging Cable User Manual	None
1 PV120/200 Panel					
AC50S 	300W 500Wh	2* AC 110V(JP/US) or 2* AC 220V-240V(EU/UK/AU) 1* Wireless Charging Port 1* PD USB-C Port (45W Max) 4* 5V/3A USB-A Port 2* 12V/3A DC-Ports 1* 12V/10A Car Port 1* LED Lantern	1. Automobile-level 3C High Rate Battery Cell 2. Pure Sine Wave AC Inverter 3. Charge 11 devices simultaneously 4. Four Recharge Ways: Wall Outlet, Solar, Car, Generator 5. Solar Input: OCV 14-40V, 120W/10A, Built-in MPPT 6. Size&Weight: 11.6*7.5*7.1inch,13.6lbs	AC50S Portable Power Station AC Adapter Car Charging Cable Solar Charging Cable USB-C Cable Manual	None
1 PV120 Panel					
EB240 	1000W 2400Wh	2* AC 100-120V(JP/US) or 2* AC 220V-240V(EU/UK/AU) 1* 12V/9A Car Port 4* 5V/3A USB Output Ports 1* 45W Type-C PD Output Port	1. Automobile-level 3C High Rate Battery Cell 2. Solar Input: 500W, OCV 16-68V, 10A, Built-in MPPT 3. Four Recharge Ways: AC Wall Outlet, Solar, Car, Generator 4. Size&Weight: 19.4*6.5*14.4inch, 48.5lb	EB240 Portable Power Station AC Charger Solar Charging Cable User Manual	None
2 PV120/PV200 Panels					
EB150 	1000W 1500Wh	2* AC 100-120V(JP/US) or 2* AC 220V-240V(EU/UK/AU) 1* 12V/9A DC Port 1* 45W PD USB-C Port 4* 5V/3A USB-A Ports	1. Automobile-level 3C High Rate Battery Cell 2. Solar Input: 500W, OCV 16-68V, 10A Max. Built-in MPPT 3. Four Recharge Ways: AC Wall Outlet, Solar, Car, Generator 4. Size&Weight: 14.6*6.5*14.4inch, 37.9lb	EB150 Portable Power Station AC Charger Solar Charging Cable User Manual	None
2 PV120/PV200 Panels					
K3 	133Wh	1* 16.8V/4.6A DC 1* PD 2.0 Type C(In&Out) 2* USB-A 5V/2.1A	1. Capacity 133.2Wh, 36000mAh 2. Designed for USB-C Laptops 3. Recharge from AC Wall Outlet/USB-C	K3 36000mAh Power Bank USB-Type C Connector DC to MacBook T Connector DC to MacBook F Connector Multifunction Bag User Manual	None